Neural Networks as Self-Learning Image Features

A practical approach

Ordwin Notten

Catholic University of Nijmegen,
The Netherlands
University Hospital Nijmegen
Biophysics Laboratory
Department of Ophthalmology

Faculty of Mathematics and Informatics
Department of Computing Science
Experimental Informatics for Technical Applications

Master's Thesis, number **370**
April 1996

Preface

This thesis is the result of my graduation project to receive my Master's degree in Computer Science at the Catholic University of Nijmegen. This project which ran from September 1995 to April 1996, was a cooperation of the Department of Computing Science and the Biophysics Laboratory of the Department of Ophthalmology of the University Hospital Nijmegen.

The goal of this project was trying to develop a practical system that can learn its own image features to improve medical diagnostics and to find out if it can be used in practise. This goal was tackled by using a neural network strategy able to produce self learning image features, solving some practical problems and evaluating its practical use.

At this point I want to thank dr. ir. Han Thijssen, ir. Henkjan Huisman and dr. Theo Schouten, my supervisors at the Biophysics Laboratory and the Computer Science department respectively, for their support, advice and help. Furthermore, I like to thank the other people of the Biophysics Laboratory, my family and friends for their support and help.

Ordwin Notten
Nijmegen, April 1996

Contents

1. Introduction

At the Biophysics Laboratory of the Department of Ophthalmology at the University Hospital Nijmegen research is done in the fields of electrophysiology and ultrasound diagnostics. For the project: “Processing of echographic images” current research is directed to images with local lesions. These images are viewed by specialists to detect these abnormalities. However, a lesion is difficult to detect, therefore research is done to find new image features that enhance the diagnostics of detecting lesions. Maximizing information tends to using as many image features as possible. However, to prevent the peaking phenomenon[1] a classifier requires a low number of features. Therefore, feature reduction is often necessary. The problem that arises is which and how many image features have to be used for classification purposes. Reducing the number of features with a minimum of information loss means that every image feature has to contain as much information as possible with relation to the diagnostics. The remaining information could be explained as noise which is undesirable. Further, every image feature has to contain as much discriminating information as possible, compared to the other image features, otherwise the information contained in the sum of image features does not achieve its maximum. The “known” image features that meet these requirements are strongly problem dependent, sometimes difficult to find and hardly optimal. When a researcher has enough knowledge about a problem he could build his own image features. However, these would also be problem dependent. Using a self learning method that is capable to calculate every image feature by itself, then an optimum feature-set could be found for every problem.

Research has been done at the laboratory to implement this idea using a neural network strategy. The reason for choosing a neural network strategy is that it can learn any input-output relation (e.q. a feature) if it is large enough. In this research [Reijnen, 1994] a literature study was performed and several neural network strategies were compared. As a result of this research an operational strategy was found that was able to produce self learning image features. It did need tremendously large, unpracticable training sets, thus the goal attached to this thesis is trying to develop this strategy into a practical system.

This thesis gives a survey and the results of the consecutive steps that were performed during the development of this practical system.
In chapter 2 the background theory about ultrasound is explained. This chapter describes what ultrasound is and how to generate it. Besides that, it explains why and how ultrasound is being used in medical diagnostics. Finally, the backgrounds are given of representing data in ultrasonic images. Chapter 3 gives the background theory about a class of neural networks which is being used in this thesis: higher order neural networks(HONN). This chapter describes the history of higher order neural networks, the theory behind these networks and the advantage of a HONN. In chapter 4 the identified problems for this thesis are described. Chapter 5 describes an overview of the system. In chapter 6 a study is done for the HONN pre-processing. Chapter 7 describes the evaluation of the self learning image feature-system. In chapter 8 conclusions concerning the goal attached to this thesis and recommendations for further research are given.

[1] Given a finite size training set. The overall unconditional error rate of a classifier will first decrease when the number of features is increased. However, beyond a certain number of features, depending on the size of the dataset, the error rate will increase.

2. Ultrasound

In this chapter some background information is given on ultrasound. The first section gives an introduction to ultrasound, such as what it is and where to place it. In the rest of the sections some frequently used terms concerning this subject are explained. The second section describes the transducer, which is used to generate and receive sound-waves. In the third section the inhomogeneities in biological tissue are described. Knowledge about these inhomogeneities is important for the understanding of images that will be introduced in the fifth paragraph. The fourth section explains the beam that is generated by the transducer. Finally the fifth section describes some types of images that can be produced by the data received from the transducer.

2.1 Introduction to ultrasound

The science of sounds is called the science of acoustics. It comprises all mechanical waves of all possible frequencies and in all possible materials. A mechanical wave is a systematic disturbance of the condition of rest of a material that changes its position in space during a lapse in time.

Sound can be divided into three frequency areas.

1. Infrasonics.
   The sound with frequencies that are too low to be heard by humans.
2. Audiosonics.
   The sound that can be heard by humans.
3. Ultrasonics.
   The sound with frequencies that are too high to be heard by humans.

In medical diagnostics ultrasound with a frequency-area between 1 and 50 MHz is used. The ultrasound-wave is generated and received by a transducer.

2.2 Transducer

Most transducers contain one or more pieces of material that exhibits the piëzo-electrical effect. This means that when a voltage is applied to that material a sound-wave will be generated caused by the volume change in that material. The opposite is also possible, when a sound-wave is entering a transducer, the volume of the material changes and a voltage is generated. So, a transducer can act as a sender and as a receiver of ultrasound.

In medical diagnostics, ultrasound is used in biological tissue that has a non-homogeneous composition. When sending ultrasound through a non-homogeneous medium backscattered echoes will be generated. If this ultrasound is emitted as a short pulse, and shortly afterwards echo-signals are received by the same transducer then we speak of a process known as the pulse-echo method.

2.3 Biological tissue

A biological tissue has a non-homogeneous composition. An inhomogeneity can be defined as: 'A particle with a different acoustical impedance than the surrounding tissue.'. These inhomogeneities vibrate under the influence of incident sound-waves. There are two kinds of inhomogeneities, namely reflectors and scatterers. These will be explained below.

Reflectors

Inhomogeneities that are much larger than the ultrasound wavelength are called reflectors. Examples for this kind of inhomogeneities are blood vessels, organs, tumors, etc. In figure 2.1 an example of a reflector is given.



Figure 2.1 Reflector

Scatterers

Inhomogeneities that are small compared to the ultrasound wavelength are called scatterers. If ultrasound hits a scatterer, the ultrasonic wave is scattered in all directions. The amount of scattering is dependent on the type of tissues, such as the size and density of the scatterers, and the frequency of the ultrasound. Some of these scatterer echoes[2] are received by the transducer that will display them as inhomogeneities in the ultrasonic-image. These scatterer echoes are also known as the backscattering echoes. In figure 2.2 [Thijssen et al., 1990] an example of a scatterer is given. The part that is scattered back to the transducer is used for imaging.



Figure 2.2 Scattering by small structures yields small omni-directional wave-fronts.

[2] The scatterer echoes that have a degree of 180° with respect to the direction in which the beam is transmitted.

Absorption

Part of the energy of the ultrasonic wave that travels through the tissue is transformed into heat. As mentioned in [Thijssen et al., 1990] absorption arises during the rapid pressure changes in the sound-waves. The more pressure changes in a time span (the higher the frequency) the higher the absorption. The higher the absorption the less energy there is left for reflection. The absorption is governed by the relaxation processes in biological molecules. Therefore the absorption is dependent on the type of tissue.

2.4 Ultrasonic beam shape

The intensity of ultrasound transmitted by a transducer is not the same in every direction. The transducer transmits it into a specific direction. The width of this beam depends on the distance to the transducer. A distinction is made between the Fresnel-zone and the Fraunhofer-zone.
A picture of this beam is given in figure 2.3 [Reijnen, 1994].



Figure 2.3 Ultrasonic beamshape

Fresnel-zone

The Fresnel-zone, also called the near-zone, is the sound field at a short distance from the transducer. The length of this near-zone is dependent on the size of the active surface of the transducer and the used wave-length. The width of the sound beam is proportional to the width of the transducer. Sound vibrations that arrive at a particular point in the Fresnel-zone can amplify or weaken each other [Thijssen et al., 1990]. This is possible because the vibrations, from the different parts of the transducer, arrive at a particular point in the Fresnel-zone at different times (due to the wavelength and the difference in distance). This is also known as interference.

Fraunhofer-zone

The Fraunhofer-zone, also called the far-zone, is the sound field at a large distance from the transducer. This beam diverges slowly. The transition from the near-zone to the far-zone is reached on the point where the difference in wavelength from the side of the transducer compared with the center of the transducer is exactly ½ λ(wavelength). This point can be calculated by $d^2 / (4*\lambda)$.

2.5 Ultrasonic images

There are different ways of imaging ultrasound. Two types will be explained.

A-mode images

An A-mode image is a one-dimensional representation of the amplitude of the echoes as a function of the depth. It is the simplest representation of RF-signals.

Before such an image is constructed, the RF-signal has undergone two operations:
1. Amplification.
   This is a time dependent compensation, also known as TGC (Time Gain Compensation), which can be in a non-linear way. It is used to compensate for the total loss of energy per unit length from the ultrasound wave as it is propagated through tissue. With this method echo signals received early in time are amplified slightly and echo signals received later in time are amplified more. In this way all the echo signals have more or less the same strength which is needed to anticipate saturation and loss of echo signals in the echogram.
2. Envelop detection.
   In this operation the signal is demodulated and filtered.

The result of these operations is visualized in figure 2.4 [Thijssen et al., 1991] which is related to Figure 2.2.



Figure 2.4 Construction of an A-mode image. The phase-sensitive sum of the backscattered echoes of the four scatterers is the RF-signal. The dotted line superimposed on the RF-signal is the envelop signal.

B-mode images

A B-mode image is a successive depiction of a series of A-mode images, whereby the amplitude is represented by brightness. By adding this second dimension the anatomical information of the image increases.

B-mode images display, first of all, the position and size of organs. In most cases there is a transition of acoustic properties between the different tissues. Due to these transitions parts of the ultrasound will be reflected. When a structure, for instance a liver, has enough transitions surrounding the whole structure then the structure can be seen in a B-mode image. An example of a B-mode image is given in figure 2.5.



Figure 2.5 B-mode image

In this image you see the liver, surrounded by a solid line, and some blood-vessels in the small ellipses.

2.6 Speckle

Tissues that are expected to be homogeneous are covered with some kind of texture, which is called speckle, resulting from the scattering in that tissue, and not noise. The speckle pattern in an image depends on the characteristics of the tissue scanned and the imaging system [Oosterveld, 1984]. This pattern does not need to have a one-to-one correspondence with echo-producing targets. As an example, consider figure 2.2: a transducer insonating a homogeneous medium that contains four point-like scatterers. These scatterers yield small omni-directional waves that arrive at slightly different times after the transmission of the ultrasound pulse at the transducer. As shown in figure 2.4 the four rf echoes will build an interference pattern, because the depth differences of the scatterers are smaller than the pulse length. The dashed line is the demodulated rf-signal that contains three peaks. Speckle can be described by using first- and second-order statistics [Wagner et al., 1983]. First-order statistics include the mean amplitude and the signal-to-noise ratio. The second-order statistics include the auto-covariance in both axial and lateral directions.

3. Higher Order Neural Networks (HONN) as SLFs

In this chapter some background information on higher order neural networks is given. The first section gives an introduction to higher order neural networks. In the second section the theory behind neural networks and the HONN is explained. The third section explains the combination of HONN and the invariances. In the last section some interconnection techniques, to solve the interconnection problem for higher order neural networks, are described.

3.1 Introduction to Higher Order Neural Networks

Since World War II, scientists have tried to develop techniques that allow computers to behave more like human beings. As mentioned in [Doolen et al., 1986] the research effort that usually goes by the fanciful name of "Artificial Intelligence", typically involves abstract problem solving, decision making, planning, machine learning and natural language understanding.

In the 1960's research was done into neural networks. This research concentrated on determining the usefulness of the perceptron for non-linear discrimination of data into classes representing the objects to be identified. It was concluded that a single-layer, first-order network was limited to linear discrimination and that either a multi-layer, first-order network or a single-layer, higher-order network was necessary for non-linear discrimination. At that time no satisfactory ways of training multi-layer, first-order networks were at hand. Higher-order neural networks were rejected as impractical due to the combinatoric explosion of higher-order terms.

Research from a few years ago has shown that multi-layer, first-order networks using the backpropagation algorithm for training are effective for distortion invariant pattern recognition. However, backpropagation trained networks require a large number of training passes and an exhaustive training set, but are still not achieving a 100 % recognition accuracy. Research on HONNs [Giles et al.,1987], [Giles et al., 1988], [Reid et al., 1989b] and [Linhart et al., 1992] has shown that the problem of combinatoric explosion of interconnections can be overcome. This can be done by building invariances into the architecture of the network using information about the relationships expected between the input nodes. The number of interconnections is usually [Giles et al., 1988] reduced by orders of powers of N, where N is the size of the input.

3.2 Theory behind HONNs

Neural networks are being used more and more. This is due to the learning properties of a neural network, by which it can be tuned to specific problem area's.

A neural network of the first order, abbreviated as FONN, can be formulated as:

$$y_i = \Theta\left(\sum_j w_{ij} x_j \right)$$

where :

Θ	is a translation function that can be non-linear (i.e. a threshold-function).
x_j	input node j
w_{ij}	matrix with the weight of each input
y_i	output of node i

This ANN does not take advantage of any known relationships between the input nodes, so translation, scale and rotation invariance are not present. Multi-layer, first order networks and higher-order neural networks are known that they can learn invariances. Multi-layer, first order networks will not be mentioned further on due to their large number of training passes and not full recognition accuracy, as mentioned above.

Following [Reid et al., 1989a] and [Reid et al., 1989b] the output of nodes in a general higher order network is given by:

$$y_i = \Theta\left(\sum_j w_{ij} x_j + \sum_j \sum_k w_{ijk} x_j x_k + \sum_j \sum_k \sum_l w_{ijkl} x_j x_k x_l + \dots \right)$$

A direct implementation (see figure 3.1) of a HONN [Huisman et al., 1995] is still impractical, because of a combinatoric explosion of higher order products. Incorporating invariances leads to translation invariant higher order transformations (see figure 3.2).



Figure 3.1 Theory HONN



Figure 3.2 Practical implementation

Higher-order neural networks can perform the non-linear discrimination required for pattern recognition invariant to scale, translation and rotation. As mentioned above, the combinatoric explosion of interconnection problems with HONNs can be overcome by building invariances into the network architecture. In general translation invariance requires that:

$$w_{ijk} = w_{i(j-k)}$$

i.e.: the connections for equally spaced input pairs are all set equal.

A second-order neural network will be simultaneously invariant to scale and translation if the weights are set according to the function [Giles et al., 1988]:

$$W(i,j,k) = W\left(i,\left(y_k - y_j\right)\Big/\left(x_k - x_j\right)\right)$$

This implies that W_{ijk} is set equal to $W_{ij'k'}$ if the line drawn in figure 3.3 between j and k equals the line between j' and k'.



Figure 3.3 Translation and scale invariance

Rotational invariance can be included by using a third-order neural network, where the output is given by the function:

$$y_i = \Theta\left(\sum_j \sum_k \sum_l w_{ijkl}\, x_j\, x_k\, x_l\right)$$

Figure 3.4 shows all three invariances. As stated by [Reid et al., 1989a] and [Reid et al., 1989b] invariances to all three distortions can be achieved with a third-order network having an interconnection function of the form:

$$w_{ijkl} = w_{i\alpha\beta\gamma} = w_{i\gamma\alpha\beta} = w_{i\beta\gamma\alpha}$$



Figure 3.4 Translation, scale and rotation invariance are achieved by setting all third order weights equal for sets of inputs j, k and l that form similar triangles.

3.3 HONNs and invariance

As stated in [Reid et al., 1989a] HONNs are thus well suited for invariant pattern recognition because feature extraction is functionally built into the architecture. The invariances achieved require no learning to produce and apply to any input pattern learned by the network. Further [Reid et al., 1989b], a HONN can perform non-linear discrimination using only a single layer so that a simple perceptron learning rule can be used, leading to rapid convergence.

Recent research [Reijnen, 1994] has shown that HONNs can also be used for image processing as self-learning image features. As stated in [Huisman et al., 1995] a properly chosen HONN implementation operates as well as, or even better than, a properly chosen set of fixed features. As an example, translation invariance can be built into the second-order neural network with 4 nodes and 1 output node shown in figure 3.5. Assume that the input patterns (1010) and (0101) are to be identified as the same object. If $W_{i13} = W_{i24}$ then Y_i is the same for both inputs. Combinations of invariances can similarly be achieved.



Figure 3.5 Second order neural network

According to [Schmidt et al, 1993] HONNs are a form of pre-processing for neural networks with the standard backpropagation that use geometrically motivated non-linear combinations of scene pixels to achieve invariant pattern recognition feature spaces.

They show that it is possible to directly incorporate geometric invariance properties such as translation and rotation invariance into the HONN if the HONN pixel combinations are properly chosen.

3.4 Non-fully interconnected techniques

Building invariances into the network, to overcome the problem of combinatoric explosion of interconnections in HONNs as mentioned above, greatly reduces the number of independent weights that must be learned. Although this also reduces the required storage space, some data still has to be stored. In a third-order neural network each triplet (for scale, translation and rotation invariance) of inputs has to be associated to a set of included angles. The most severe limitation that arises is that as the size of the input field increases, the number of triplet combinations that can be formed also increases. In a NxN pixel input field, three pixels can be combined in $(N^2)^3$ ways. Thus, for a 9x9 pixel input field, the number of combinations is 81^3 or 85,320. By increasing the resolution to 128x128 pixels, the number of combinations increases to $(128^2)^3$ or 7.3×10^{11}, a number too large to store on most machines.

To solve this interconnection problem, [Reid et al, 1990] have been evaluating various methods of connecting only a subset of input pixel triplets to the output node. They have evaluated four techniques, namely local, sampled, probabilistic and regional connectivity. These will be explained below.

Local connectivity

The assumption behind local connectivity is that local connections are adequate for distinguishing between objects and that distant information will be represented by some combination of local information. Thus, a connection for a triplet of pixels is formed only if all three pixels are within some bounded number of pixels away from each other.

Sampled connectivity

The assumption behind this technique is that only a fraction of all possible input pixel triplets are connected to the output. This fraction is not a function of the distance between the pixels, but a predetermined subset of interconnections.

Probabilistic connectivity

This method tries to improve on local connectivity, the images are sampled using a technique in which the probability of connection varies with distance.

Regional connectivity

This method combines the advantages of the other approaches while eliminating their disadvantages. Here, triplets of pixels are connected to the output only if the distance between all of the pixels falls within a set of pre-selected regions. These regions are chosen so as to sample the space sufficiently for accurate discrimination. Thus, triplets are formed from pixels that are local, distant and in-between. Because the connections are deterministic, it is guaranteed that the same information will be sampled from a test image, which may be rotated or translated, as from a training image. Besides the advantages of this technique there also is a disadvantage, namely that some experimentation's are needed to determine an optimal set of regions.

4. Problem definition

In this chapter the problems contained in this thesis will be identified and solutions, to solve these problems, will be searched. The goal attached to this thesis is trying to develop a neural network strategy that is able to produce self learning image features into a system. To achieve this goal several questions concerning the problems have to be answered. Each of these questions will be discussed separately.

1. How to construct a good pre-processing unit? And which theories can best be used for it.
   The reason to use a pre-processing unit in the HONN is to reduce the input for the neural network to speedup the training process of the neural network. By reducing the dimensionality of the input for the neural network the number of needed training examples can also be reduced. Although reduction means data loss it does not imply that it is important data, but to make sure the following questions have to be answered: Which parts of the input may or may not be reduced? How to determine a pre-processing unit? How to verify that it is a good pre-processing unit? What is the maximum allowable reduction factor? To answer these questions, a study concerning this subject has to be done.

2. What size of window is used to focus on the image?
   Although the size of the window depends on the lesion chosen to be detected, it may not be too small or too large. If the size of the window is too small then a good resolution would be obtained, but a worse statistic. Making the window too big would mean a good statistic, but a worse resolution. The solution is to find a window size or a range of window sizes that have a good statistic and a good or reasonable resolution.

3. How long does a neural network have to learn?
   If a neural network is not trained long enough it is not able to classify correctly. On the other hand the possibility exists that the neural network is trained too long, so that it will not be able to classify new data: i.e. overlearning occurs. To determine how long a neural network has to learn, the following questions arise: How many training examples are statistically needed to learn a neural network to distinguish between the possibilities of a particular problem? How can be determined that the neural network has learned enough, and not too less or too much? A solution to test the trained neural network is to use an independent validation set to find out how good it classifies it.

4. Which labels will be assigned?
   To train a neural network to distinguish between different image regions, several example windows from these regions are required. Each window in the training set should have a label corresponding to the region to which it belongs. A question that arises: How to determine the label of a window? A solution for this is to use a function that estimates the label from an accompanying mask image.

5. What size of network will be taken? Meaning number of hidden layers etc.

When using a small neural network, for instance without a hidden layer, then the neural network can easily, depending on the dimensionality of the input, determine its weights. Using a larger neural network it becomes harder for the neural network to determine its weights, because a larger set of training examples are needed. However, the large neural network can learn more from the training set. A solution to take advantage of a larger, with for instance 1 or 2 hidden layers, neural network is to use a low dimensionality of input for the neural network.

6. How to incorporate the SLF (Self-Learning Image Features) into a practical system?
   Developing a practical system that can produce and use self learning image features needs a neural network. To let a neural network determine its own image features, the neural network has to learn to detect such image features. Therefore it has to learn the characteristics of those features. Questions that arise: How to develop such a system? What are the requirements of the system? Which programming language will be used? Are neural networks available in that programming language? And on which hardware will the system be developed? Answers for these questions will be given in chapter 5.

Not every question can be answered that easily, therefore the necessary studies have to be done, but first a design of the system will be constructed.

5. SLF System development

In this chapter the system for the image processing and analysis will be described. The first section will list the system requirements. In the second section a possible system design will be shown according to the system requirements.

5.1 Requirements

Before a system design can be developed and accepted the requirements have to be clear.

- All the different system-parts have to be separate units or modules.
- The system has to be developed in a modular way without having effect on the operation of the whole system. This means that units can easily be replaced by other units, for example replacing the pre-processing unit with another pre-processing unit.
- The system needs two kinds of batch-modes, one to let the system learn and one to let the system evaluate. In the learn mode the system will receive training images and their corresponding mask images to train the neural network. During the evaluation mode the neural network will evaluate the input images using its learned initialization.
- For test-facilities it is further desirable that all the units can be executed separately. For this purpose, the system should have a separate interface-window or control-unit where the user can execute them by prompt.
- The system will work with windows, or parts of the image, to perform the operations on.
- For image analysis several functions should be possible to apply to the images in the image processing part.

The system will be developed on a SUN workstation using the programming language MATLAB, a high-performance numeric computation and visualization programming language. Two reasons why MATLAB is chosen as programming language:
1. MATLAB is a modular based programming language with an experimental environment. Therefore it is easy to perform tests on separate units.
2. The programming language and knowledge about MATLAB are available in the laboratory.

5.2 System design

In this section a possible system design, according to the system requirements mentioned in section 5.1, will be given. Flowcharts and some explanation will be used to describe (part of) the system. Before a possible system design is presented, an explanation of the used symbols is given (see figure 5.1).



Figure 5.1 Symbol explanation

Now that the symbols, used in the flowcharts, are explained the flowcharts that describe the system can be presented. First an overview and description of the total system will be given. After that, the flowcharts of each process are presented.



Figure 5.2 System overview

In figure 5.2 the overview of the total system is given. This flowchart contains two processes; the 'Image Processing'-process (6) and the 'Image Analysis'-process (7). The 'Image Processing'-process (6) processes a test image according to the accompanying functions and delivers an output image for every function. The 'Image Analysis'-process (7) analyses the classification of each image that results in an output. Each of these processes will be described in detail further on. The mask image of a test image is in the 'Image Processing'-process (6) being used to train a neural network. In the 'Image Analysis'-process (7) this mask image is being used to analyze the classification of the test image by the neural network.

To explain the 'Image Processing'-process (6) further the flowchart describing this process will be used. The flowchart of this process is shown in figure 5.3.



Figure 5.3 Image Processing overview

The input and output of the dashed box are the same as the input and output of the 'Image Processing'-process (6) in figure 5.2 and will therefore not be mentioned here. In this flowchart the accompanying functions, to be used on the test image, are split up, meaning that for every function the 'IPF'-process (6.2) is called to determine the output image. IPF stands for Image Processing on Function level. The function control (6.3) controls the set of functions out of which a function is selected by the function selection (6.1). This function selector selects a, not yet used, function to be used on the test image, and the function projection (6.4) connects the output of the 'IPF'-process (6.2) to the used function. From the function control (6.3) there is also an arrow going directly to the 'IPF'-process (6.2). This means that inside this process there are functions being controlled by the function control (6.3), but this will be explained further on.

To explain the 'IPF'-process (6.2) further the flowchart shown in figure 5.4 will be described.



Figure 5.4 IPF overview

As shown in the upper right corner of the dashed box in figure 5.4 this box represents the ‘IPF’-process (6.2). In this figure some of the lines going to and coming from the processes have a dashed line, this means that only a subset of all processes have been put in this flowchart. The function selection (6.1) has one output-line with arrows on each process, this means that depending on the selected function the corresponding process will be evaluated, that uses the test image as input. For the output only the evaluated process will deliver data for the function projection (6.4). The process ‘Self Learning Feature’ (6.2.1) has more inputs compared to the other processes. This process uses the mask image to train the neural network and the function control (6.3) to control the functions used in this process. The processes ‘Average’ (6.2.3) and ‘Variance’ (6.2.2) are known parameters on images, and will therefore not be mentioned further.

The ‘Self Learning Feature’-process (6.2.1) will be explained by using the flowchart shown in figure 5.5.



Figure 5.5 SLF overview

The function control (6.3) controls the pre-process function (6.2.1.3) and the label function (6.2.1.4) to be able to use other pre-processing or label functions. In this flowchart the images are split up into windows using a number of pixels horizontal and/or vertical as distance between the windows. The window control (6.2.1.5) controls the set of windows from the test image and the mask image, the window selection (6.2.1.1 and 6.2.1.2) selects a window from the test image and the mask image, and the window projection (6.2.1.7) connects the output of the ANN (6.2.1.6) to the selected window to construct a new image. This flowchart comprises two batch modes; the training mode to train the neural network and the operational mode to evaluate a test image. In the training mode[3] four steps are taken. First a window is selected from the test image and its mask image. Second, the window from the test image is being pre-processed to reduce the dimensionality of the window. Then the label function calculates a label from the window of the mask image. Several functions are possible for the label function[4]. In this thesis a 95 % rule is used to determine the label of a window. Windows that have a lower percentage receive an undefined label and will not be used in training. In the last step the neural network gets the pre-processed window and the calculated label as input. The neural network has to learn the pre-processed window so that, when evaluating this window, the calculated label is its answer. In the operational mode[5] the steps taken are almost the same as during the training mode except that in the operational mode the path from mask image (3) to ANN (6.2.1.6) is not used, because in this mode the neural network uses its learned data. For the ANN a feed forward neural network will be used.

[3] The used matlab script is present in appendix C as: “train_nn.m”.
[4] The used matlab script is present in appendix C as: “labelmask.m”.
[5] The used matlab script is present in appendix C as: “use_nn.m”.



Figure 5.6 Image Analysis overview

Besides the 'Image Processing'-process (6) the flowchart shown in figure 5.2 contained also an 'Image Analysis'-process (7). The flowchart describing this process is shown in figure 5.6. In this flowchart the accompanying functions and their images are split up to perform a classification analysis between functions or images that results in an output analysis. This can, for instance, be a classification analysis between the average and variance and its classes or between the output of the neural network from a test image and its mask image.

6. SLF Pre-processing

In chapter 5 'SLF System development' the self learning image feature (SLF) was described. It contains a higher order neural network (HONN) that was constructed from a pre-processing part and an artificial neural network (ANN). The reason to use a HONN is that it reduces the size of a neural network compared to the 'brute force approach', that will not be described here. This reduction is possible because no training is required to achieve invariances as they can be built into the architecture of the network. The pre-processor selects part of the higher order terms. After pre-processing these, these will result in for instance a histogram, an auto-covariance, or a co-occurrence. Besides these transformations several other transformations can be used, such as those used in the ultrasound (i.e. backscatterspectrum).

The above approach has been tested [Huisman et al., 1995], but was not suited to be used in a practical situation because the transformation still resulted in a high dimensional input to the ANN. Two problems arise due to the high dimensional input:

1. By using the transformation on local windows in an image, as described in the previous chapter, an upper bound is introduced to the number of transformed values in making a statistical correct estimate. The reason for this results from the limited set of values in a window (i.e. a 10 x 10 window with 100 values is not suited to estimate a histogram with 256 bins).
2. The neural network itself is the second problem. Using a large number of inputs results in a large number of weights and when training a neural network to obtain a low generalization error, one needs a large number of training examples. As stated by [Hertz et al., 1993] the number of training examples has to be an order of magnitude larger than the number of weights (10, $=(0.1)^{-1}$, to expect a generalization error less than 0.1 (=10 %)). So when training a neural network with no hidden layers, 256 input neurons and a generalization error expectation of less than 10 % then 256 x $(0.1)^{-1}$ = 2560 uncorrelated windows are needed. Using a neural network with 1 hidden layer that has 256 neurons then 256 x 256 x $(0.1)^{-1}$ = 655360 uncorrelated windows are needed. This would result in a practically unfeasible set of data to be learned by a neural network.

A solution to this problem has to be found in the reduction of the dimension of the transformation.

This chapter describes a method to reduce the dimensionality of the pre-processed data. To test this method several experiments have been done. In the first section a description will be given of the reduction problem: difference-information loss. The second section will describe a method to quantify the difference-information and a necessary pre-transformation step to prevent unwanted conditions in the quantification method. In the third section experiments are done to find out if a pre-reduction can be done. The fourth section describes the methods used to reduce the high dimensional input to the ANN. In the fifth section the results from 8 experiments are shown. The sixth section gives a total overview of the HONN pre-processing. In the last section a summary resulting from the HONN pre-processing study is presented.

6.1 Information

In the introduction of this chapter the term experiment was used. During this study several experiments will be done. For the first experiment images will be used that have a Gaussian distribution with the following characteristics:

- $\mu = 0$ and $\sigma = 1$, further on called type I images.
- $\mu = 0$ and $\sigma = 2$, further on called type II images.

An example image, and its mask image, are shown in figure 6.1 and figure 6.2. In these figures the upper part is of type I and the lower part of type II.

For these experiments a window size of 5x5 is used. To determine if a window is of type I or of type II, the mask pixels in that window are evaluated. A requirement to classify a window as type I or type II is that the pixels of the mask window are uniformly labeled. For every image such a mask image is included.

In order to find methods to reduce the dimension of the transformation it is necessary to know what may and may not be reduced. For this study the choice has been made to use the histogram transformation. To be able to distinguish two types of histograms, they should be different. When this difference decreases, the two types of histograms become harder to distinguish. This difference will be called the difference-information from the two types of histograms. Because this difference is used to distinguish the two histograms, the transformation has to minimize the loss of the difference. As an example the difference histogram[6] of experiment 1 will be shown. Before this histogram can be produced, the histograms of type I and of type II have to be calculated. To get a good representative histogram of type I, a large set of type I histograms has to be averaged. A set of 100 images with 48 windows each has been used. Because for each window a histogram is calculated, this results in 100 x 48 = 4800 histograms of type I. The same procedure has been followed to determine a mean histogram of type II.



Figure 6.1 Example image with type I and type II data



Figure 6.2 Mask image of figure 6.1

[6] The used matlab script is present in appendix C as: “verschilhist.m”.

The average histograms of type I and type II are shown in figure 6.3a and figure 6.3b. The difference, subtracting type II from type I, is shown in figure 6.3c. It shows were the difference-information concerning the discrimination between the two histograms is located.



Figure 6.3 a) average histogram type I with window 5x5 and #bins=256.
b) average histogram type II with window 5x5 and #bins=256.
c) difference (type I - type II) histogram with window 5x5 and #bins=256.

In the above examples 256 bins were used to determine the histograms. However, this requires a large number of windows. The two problems, as stated in the introduction of this chapter, are not solved in this situation. A possible solution has to be found in the reduction of the number of bins. The kind of impact this would have on the difference-information is unknown, therefore a method to quantify the difference-information has to be found. This will be done in the following section.

6.2 Difference-information quantification

The amount of difference-information, contained in the difference between the two histograms, is low if the difference is small and increases if the difference is growing. A method that uses this difference is the chi-square-test[7] [Papoulis, 1991]. It was designed to test the difference between a histogram and a known distribution of occurrences. This known distribution of occurrences could be interpreted as a special kind of histogram. Namely, one from whom the distribution of occurrences is known, and seems therefore suitable in this situation. The chi-square-test uses the following formula:

[7] The used matlab script is present in appendix C as: “chi_square.m”.

$$\chi^2 = \sum_{i=1}^{M} \frac{\left(K_i - NP_{0,i}\right)^2}{NP_{0,i}} \tag{1}$$

where

χ^2 : Average chi-square
K_i : Number of occurrences in bin i
N : Total number of occurrences
$P_{0,i}$: Probability of an occurrence in bin i

However, for this situation the above Eq. 1 has a disadvantage. When NP_0 is interpreted as a histogram then it calculates an asymmetric difference between the occurrences of two histograms. As an example figure 6.3a and figure 6.3b could be used as K and NP_0 in this chi-square formula that results in a chi-square value x. Using figure 6.3a as NP_0 and figure 6.3b as K in the chi-square formula would result in a chi-square value different from x. Therefore the following symmetric interpretation of the chi-square-test is used:

$$\chi^2 = \sum_{i=1}^{M} \frac{\left(K_{1,i} - K_{2,i}\right)^2}{\left(K_{1,i} + K_{2,i}\right)/2} \tag{2}$$

where

χ^2 : Average chi-square
$K_{1,i}$: Occurrences of bin i in histogram 1
$K_{2,i}$: Occurrences of bin i in histogram 2

The histograms shown in the previous section were calculated using a linear bin-distribution for the histogram-function. As result of this it is possible that some bins in the denominator of equation 2 are very small. These small denominator values blow up the chi-square value. Therefore, the chi-square value becomes highly sensitive to noise (see figure 6.3c). If this occurs the chi-square-test would be useless, because the chi-square values would not converge to an optimum. To solve this problem, two solutions can be distinguished. The first solution would be to generate more test images to increase the number of occurrences at those bins that are not likely to occur. This in turn will increase the test size that was set out to be kept small. The second solution is to prevent the denominator to become very small by applying a transformation on the denominator.

The transformation, called the pre-transformation, that realizes this requirement is the equalization transformation on the denominator of the chi-square-test. This transformation will try to equalize the occurrences in the denominator by assigning a non-linear bin-distribution. The equalization transformation results in an equalized bin-distribution of the sum of the two histograms to get a correct denominator in the chi-square-test. However, performing an equalization transformation without obtaining 'holes' [Gonzalez et al., 1987] in the histograms requires that images have been digitized in floating point precision. Visualizing the pre-transformation[8] results in figure 6.4.



Figure 6.4 Pre-transformation

To summarize this section on how to calculate the difference-information between two histograms. The first step is to determine the equalization transformation[9] that is derived from the average sum of the two histograms. Second is to apply this transformation on both the input histograms. The third step is to use the transformed[10] histograms on Eq. 2 that calculates an estimate of the difference-information between these two histograms. Further is assumed that images are digitized in floating point precision.

6.3 Pre-reduction possibility

To solve the problems, as stated in the introduction of this chapter, a reduction of the number of bins is needed with a minimum of difference-information loss. At this point two possibilities can be distinguished for the reduction:
1. Reducing the number of bins during the histogram calculation
2. Reducing the number of bins during the equalization transformation.

In this section experiments are carried out to test how well the reduction performs when this is done immediately during histogram calculation or during equalization transformation. The histogram calculation as well as the equalization transformation are necessary to calculate and quantify the

[8] The used matlab script is present in appendix C as: "pre_trans.m".
[9] The used matlab script is present in appendix C as: "equtransf.m".
[10] The used matlab script is present in appendix C as: "verdeelhistdata.m".

difference-information. In the first possibility the histogram is calculated with a reduced number of bins followed by the histogram equalization. For the second possibility the histograms are calculated at maximum number of bins and a bin-reduction is achieved during the equalization. First the reduction during histogram calculation is considered. The histograms and the accompanying difference are shown in figure 6.5, figure 6.6 and figure 6.7 for a reduction to 10, 50 and 256 bins respectively.



Figure 6.5 window 5x5 and #bins=10.
a) histogram type I before equalization. b) after equalization.
c) histogram type II before equalization. d) after equalization.
e) difference histogram before equalization. f) after equalization


occurrence
a) bindistribution
occurrence
b) bindistribution
occurrence
c) bindistribution
occurrence
d) bindistribution
occurrence difference
e) bindistribution

ERROR: stackunderflow
OFFENDING COMMAND: rectclip

STACK: